

**同心, 偏心 异径管头 Reducer (Concentric, Eccentric) Specification**

Pipe Size (A Size)

OD1	OD2	A/D
15A	1/4", 3/8", 1/2", 3/4"	100
20A	1/4", 3/8", 1/2", 3/4", 15A	105
25A	1/4", 3/8", 1/2", 3/4", 1", 15A, 20A	120
32A	1/4", 3/8", 1/2", 3/4", 1", 1.5", 15A, 20A, 25A	125
40A	1/4", 3/8", 1/2", 3/4", 1", 1.5", 15A, 20A, 25A, 32A	130
50A	1/4", 3/8", 1/2", 3/4", 1", 15A, 20A, 25A, 32A, 40A	140
65A	1/4", 3/8", 1/2", 3/4", 1", 20A, 25A, 32A, 40A, 50A	165
80A	1/4", 3/8", 1/2", 3/4", 1", 20A, 25A, 32A, 40A, 50A, 65A	170
100A	1/4", 3/8", 1/2", 3/4", 1", 20A, 25A, 32A, 40A, 50A, 65A, 80A	180
125A	1/4", 3/8", 1/2", 3/4", 1", 2", 2.5", 3", 3.5", 4"	250
125A	15A, 20A, 25A, 32A, 40A, 50A, 65A, 80A, 100A	250
150A	1/4", 3/8", 1/2", 3/4", 1", 2", 2.5", 3", 3.5", 4", 5"	260
150A	15A, 20A, 25A, 32A, 40A, 50A, 65A, 80A, 100A, 125 <sup>a</sup>	260
200A	1/4", 3/8", 1/2", 3/4", 1", 2", 2.5", 3", 3.5", 4", 5", 6"	280
200A	15A, 20A, 25A, 32A, 40A, 50A, 65A, 80A, 100A, 125A, 150 <sup>a</sup>	280
250A	1/4", 3/8", 1/2", 3/4", 1", 2", 2.5", 3", 3.5", 4", 5", 6"	300
250A	15A, 20A, 25A, 32A, 40A, 50A, 65A, 80A, 100A, 125A, 150A, 200 <sup>a</sup>	300
300A	1/4", 3/8", 1/2", 3/4", 1", 2", 2.5", 3", 3.5", 4", 5", 6"	325
300A	15A, 20A, 25A, 32A, 40A, 50A, 65A, 80A, 100A, 125A, 150A, 200A, 250A	325
350A	1/4", 3/8", 1/2", 3/4", 1", 2", 2.5", 3", 3.5", 4", 5", 6"	455
350A	15A, 20A, 25A, 32A, 40A, 50A, 65A, 80A, 100A, 125A, 150A, 200A, 250A, 300A	455
400A	1/4", 3/8", 1/2", 3/4", 1", 2", 2.5", 3", 3.5", 4", 5", 6"	480
400A	15A, 20A, 25A, 32A, 40A, 50A, 65A, 80A, 100A, 125A, 150A, 200A, 250A, 300A, 350A	480

