


异径三通规格 Reducing Tee Specification

Pipe Size (A Size)

OD1	OD2	A	B
15A	1/2",3/8",1/4"	47	44
	3/4",5/8"	52	52
20A	1/2",3/8",1/4"	47	47
	15A,1",3/4",5/8"	55	55
25A	1/2",3/8",1/4"	47	50
	20A,15A,1",3/4",5/8"	59	59
32A	1/2",3/8",1/4"	57	54
	3/4",5/8"	68	62
	25A,20A,15A,1"	68	62
40A	1/2",3/8",1/4"	57	57
	25A,20A,15A,1",3/4",5/8"	68	65
	32A,1-1/2"	77	77
50A	1/2",3/8",1/4"	57	63
	25A,20A,15A,1",3/4",5/8"	68	71
	40A,32A,2",1-1/2"	83	83
65A	1/2",3/8",1/4"	61	71
	25A,20A,15A,1",3/4",5/8"	72	79
	50A,40A,32A,2",1-1/2"	88	90
	2-1/2"	97	97
80A	1/2",3/8",1/4"	61	77
	25A,20A,15A,1",3/4",5/8"	72	85
	50A,40A,32A,2",1-1/2"	88	96
	65A,3",2-1/2"	103	103
100A	1/2",3/8",1/4"	61	90
	25A,20A,15A,1",3/4",5/8"	72	98
	50A,40A,32A,2",1-1/2"	88	109
	80A,65A,4",3",2-1/2"	116	116

OD1	OD2	A	B
125A	1/2",3/8",1/4"	80	110
	25A,20A,15A,1",3/4",5/8"	100	120
	50A,40A,32A,2",1-1/2"	120	130
	100A,80A,65A,4",3",2-1/2"	140	140
	5"	160	160
150A	1/2",3/8",1/4"	90	130
	25A,20A,15A,1",3/4",5/8"	110	140
	50A,40A,32A,2",1-1/2"	130	150
	100A,80A,65A,4",3",2-1/2"	150	160
	125A	170	170
200A	1/2",3/8",1/4"	100	150
	25A,20A,15A,1",3/4",5/8"	120	160
	50A,40A,32A,2",1-1/2"	140	170
	100A,80A,65A,4",3",2-1/2"	160	180
	150A,125A	180	190
250A	1/2",3/8",1/4"	110	180
	25A,20A,15A,1",3/4"	130	190
	50A,40A,32A	150	200
	100A,80A,65A	170	210
	150A,125A	190	220
	200A	210	240
300A	1/2",3/8",1/4"	120	200
	25A,20A,15A,1",3/4"	140	210
	50A,40A,32A	160	220
	100A,80A,65A	180	230
	150A,125A	200	240
	200A,250A	220	260



Tube Size (Inch Size)

OD1	OD2	A	B
3/8"	1/4"	45	45
1/2"	3/8",1/4"	45	45
5/8"	1/2",3/8",1/4"	47	44
3/4"	1/2",3/8",1/4"	47	44
	5/8"	52	52
1"	1/2",3/8",1/4"	47	47
	3/4",5/8",15A	55	55
1-1/2"	1/2",3/8",1/4"	57	54
	1",3/4",5/8",25A,20A,15A	68	62
2"	1/2",3/8",1/4"	57	57
	1",3/4",5/8",25A,20A,15A	68	65
	1-1/2",40A,32A	77	77
2-1/2"	1/2",3/8",1/4"	61	63
	1",3/4",5/8",25A,20A,15A	72	71
	2",1-1/2",50A,40A,32A	90	83

OD1	OD2	A	B
3"	1/2",3/8",1/4"	61	71
	1",3/4",5/8",25A,20A,15A	72	79
	2",1-1/2",50A,40A,32A	90	90
	2-1/2"	97	97
4"	1/2",3/8",1/4"	61	87
	1",3/4",5/8",25A,20A,15A	72	95
	2",1-1/2",50A,40A,32A	90	105
5"	3",2-1/2",80A,65A	110	110
	1/2",3/8",1/4"	70	100
	1",3/4",5/8",25A,20A,15A	90	110
6"	2",1-1/2",50A,40A,32A	110	120
	4",3",2-1/2",100A,80A,65A	140	140
	1/2",3/8",1/4"	80	115
	1",3/4",5/8",25A,20A,15A	100	125
6"	2",1-1/2",50A,40A,32A	120	135
	4",3",2-1/2",100A,80A,65A	140	145
	5",125A	160	160